

## LX7-A-USD6

### LX7-A Option Switch Settings: 1(Pulse/ccTalk)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

LX7-A dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	SW11	SW12	SW13	SW14
★ Reject USD 1	ON													
★ Accept USD 1	OFF													
★ Reject USD 5		ON												
★ Accept USD 5		OFF												
★ Reject USD 10			ON											
★ Accept USD 10			OFF											
★ Reject USD 20				ON										
★ Accept USD 20				OFF										
★ Reject USD 50 & 100					ON									
★ Accept USD 50 & 100					OFF									
★ Reserved						ON								
★ Reserved						OFF								
★ Harness Disable							ON							
★ Harness Enable							OFF							
★ Inhibit Active High								ON						
★ Inhibit Active Low								OFF						
ccTalk Parameters(default setting) <small>(Note.4)</small>										ON				
ccTalk Parameters(User setting)										OFF				
★ 1 pulse / USD 1								OFF	OFF					
★ 2 pulses / USD 1								ON	OFF					
★ 4 pulses / USD 1								OFF	ON					
★ 20 pulses / USD 1								ON	ON					
★ Pulse Speed	50ms LO / 50ms HI									OFF	OFF			
	60ms LO / 300ms HI									ON	OFF			
	30ms LO / 50ms HI									OFF	ON			
	150ms LO / 150ms HI									ON	ON			

★ Manufacture setting

Note : (1) Default setting.  
 (2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.  
 (3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.(ccTalk ONLY)

## LX7-A-USD6(Pulse/ccTalk)

### DIP SWITCHES SETTING : 2(Pulse)

FUNCTION	SW1	SW2	SW3	SW4
★ Pulse Normal High	ON			
★ Pulse Normal Low	OFF			
★ Pulse Mode		ON		
★ ccTalk Interface		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Reserved				ON
★ Reserved				OFF

### Currency Assign Data

Interface Bill value	Pulse	ccTalk
BV1	USD 1	USD 1
BV2	USD 5	USD 5
BV3	USD 10	USD 10
BV4	USD 20	USD 20
BV5	USD 50	USD 50
BV6	USD 100	USD 100

### DIP SWITCHES SETTING : 2(ccTalk)

FUNCTION	SW1	SW2	SW3	SW4
★ 8-bit checksum	ON			
★ CRC 16-bit checksum	OFF			
★ Pulse Mode		ON		
★ ccTalk Interface		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Encryption MODE				ON
★ Decrypt MODE				OFF

★ Manufacture setting

Note : (1) Default setting.  
 (2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.  
 (3) Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.(ccTalk ONLY)