

XBA mini-USD6

XBA mini Option Switch Settings: 1(Pulse/MDB/JPSTD/ICT104U/ICT104V)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject USD 1	ON											
★ Accept USD 1	OFF											
★ Reject USD 5		ON										
★ Accept USD 5		OFF										
★ Reject USD 10			ON									
★ Accept USD 10			OFF									
★ Reject USD 20				ON								
★ Accept USD 20				OFF								
★ Reject USD 50 & 100					ON							
★ Accept USD 50 & 100					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec					ON							
★ Enable Bill Reject 4 Times BA Stop By 30 Sec					OFF							
★ Colorful light						OFF	OFF					
★ The green light flashes						OFF	ON					
★ Reserved						ON	OFF					
★ No light						ON	ON					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ Reserved								ON				
★ Reserved								OFF				
★ Interface Timing Conversion		5ms LO / 5ms HI							OFF	OFF		
		5ms LO / 10ms HI							ON	OFF		
		10ms LO / 10ms HI							OFF	ON		
		20ms LO / 20ms HI							ON	ON		

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses, you should reset the bill acceptor again.

(2) Calibration card is needed.

XBA mini-USD6(Pulse/MDB/JPSTD/ICT104U/ICT104V)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ 1 pulse / USD 1			OFF	OFF
2 pulses / USD 1			OFF	ON
4 pulses / USD 1			ON	OFF
20 pulses / USD 1			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Connect with coin changer	ON			
Connect with ICT VCCS Converter board	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting

Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ MDB Mode			OFF	OFF
★ JPSTD Mode			OFF	ON
★ ICT104U Mode			ON	OFF
★ ICT104V Mode			ON	ON

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	ICT104V	JPSTD	Pulse	MDB
BV1	1	1	1	1	1
BV2	5	5		5	
BV3	10	10		10	5
BV4	20	20		20	10
BV5	50	50		50	20
BV6	100	100		100	50
BV7					100