

## A6E-USD4

### A6E Option Switch Settings: 1 (Pulse/5V ENABLE/ICT002U)

### Supported bill US\$ 1, 5, 10, 20 4bills.

A6E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject US\$ 1	ON											
★ Accept US\$ 1	OFF											
★ Reject US\$ 5		ON										
★ Accept US\$ 5		OFF										
★ Reject US\$ 10			ON									
★ Accept US\$ 10			OFF									
★ Reject US\$ 20				ON								
★ Accept US\$ 20				OFF								
★ High Acceptance					ON							
★ High Security					OFF							
★ Interface(VCP) Mode	(Note.3)				ON							
★ Diagnostic Mode	(Note.4)				OFF							
★ Harness Disable						ON						
★ Harness Enable						OFF						
★ Inhibit Active High	(Note.5)						ON					
★ Inhibit Active Low							OFF					
★ 1 pulse / US\$ 1							OFF	OFF				
★ 2 pulses / US\$ 1							ON	OFF				
★ 4 pulses / US\$ 1							OFF	ON				
★ 20 pulses / US\$ 1							ON	ON				
★ Pulse Speed	50ms LO / 50ms HI								OFF	OFF		
	60ms LO / 300ms HI								ON	OFF		
	30ms LO / 50ms HI								OFF	ON		
	150ms LO / 150ms HI								ON	ON		

★ Manufacture setting

◆ Default setting(Factory configuration has all switches in the OFF position.)

Note : (1) Reset the bill acceptor after setting the dip switch.

(2) SW7 and SW8 of the 8-switch DIP and the 4-switch DIP are for pulse protocol only.

(3) Interface(VCP) Mode is for USB connection of ICT002U.

(4) Diagnostic Mode is for USB connection of Autotest tool.

(5) SW8 of the 8-switch DIP is for pulse 5V Enable only.

## Appendix

## A6E-USD4(Pulse/5V Enable/ICT002U)

Remove the front cover and the dip-switch is on the CPU board.

### A6E Interface Settings: 2 (Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
ICT002U Mode		OFF		
Reserved			ON	
★ Reserved			OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

### A6E Interface Settings: 4 (ICT002U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
	OFF			
★ Pulse Mode		ON		
★ ICT002U Mode		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Reserved				ON
				OFF

★ Manufacture setting

## Currency Assign Data

Interface Bill value	ICT	Pulse
BV1	US\$ 1	US\$ 1
BV2	US\$ 5	US\$ 5
BV3	US\$ 10	US\$ 10
BV4	US\$ 20	US\$ 20