

BR2300-USD7

BR2300 DIP SWITCHES SETTING : (MDB/ICT-BC/ccTalk)

Supported bill USD 1, 2, 5, 10, 20, 50, 100 7 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
Reject USD 1 & 2 & 5	ON									
★ Accept USD 1 & 2 & 5	OFF									
Reject USD 10 & 20		ON								
★ Accept USD 10 & 20		OFF								
Reject USD 50 & 100			ON							
★ Accept USD 50 & 100			OFF							
High Acceptance (Note.4)				ON						
★ High Security				OFF						
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2 (MDB Only)					ON					
★ Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0					OFF					
★ Normal						OFF	OFF			
Load Banknote to Recycle						ON	OFF			
Load Banknote to Stacker						OFF	ON			
Unload Banknote to Stacker						ON	ON			
★ ccTalk								ON	OFF	
★ ccTalk (Note.1)								OFF	ON	
★ MDB Mode								OFF	OFF	
★ ICT-BC Mode								ON	ON	
★ ccTalk	MDB Mode			ICT-BC Mode						
★ Encryption MODE	Virtual MDB Recycler Function (Note.2)			Connect with MDB Connector						ON
★ Decrypt MODE	Standard MDB Recycler Function			Connect with RS232 Connector						OFF

★ Manufacture setting

After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note.1: Turn this dip to with restart the bill acceptor will restore ccTalk address to its default value of 40 and the encryption key to its default value of 123456.

Note.2: Recycled Banknote represents virtual MDB coin type.

Note.3: Calibrate card is needed.

Note.4: High acceptance mode will increasing accepting rate, however, it will reduce the security level of Bill Acceptor.

Currency Assign Data

Interface Bill value	MDB	ICT-BC	ccTalk	Recycler banknote inventory	
BV1	USD 1	USD 1	USD 1	USD 1	40 pcs
BV2	USD 2	USD 2	USD 2	USD 2	40 pcs
BV3	USD 5	USD 5	USD 5	USD 5	40 pcs
BV4	USD 10	USD 10	USD 10	USD 10	40 pcs
BV5	USD 20	USD 20	USD 20	USD 20	40 pcs
BV6	USD 50	USD 50	USD 50	USD 50	40 pcs
BV7	USD 100	USD 100	USD 100	USD 100	40 pcs