

# S7ER-USD6 Option Switch Settings: (Pulse)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★ Reject USD 1	ON															
★ Accept USD 1	OFF															
★ Reject USD 5		ON														
★ Accept USD 5		OFF														
★ Reject USD 10			ON													
★ Accept USD 10			OFF													
★ Reject USD 20				ON												
★ Accept USD 20				OFF												
★ Reject USD 50 & 100					ON											
★ Accept USD 50 & 100					OFF											
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
★ Stack Banknote when Power-up							ON									
★ Reject Banknote when Power-up							OFF									
★ Test Mode (No Communication)								ON								
★ Operation Mode								OFF								
★ Reserved									ON							
★ Reserved									OFF							
★ Reserved										ON						
★ Reserved										OFF						
★ Reserved											ON					
★ Reserved											OFF					
★ Reserved												ON				
★ Reserved												OFF				
★ Credit-Pulse Normal HIGH										ON						
★ Credit-Pulse Normal LOW										OFF						
★ Pulse Mode													ON			
★ ICT002 Mode													OFF			
★ 1 pulse / USD 1														OFF	OFF	
★ 2 pulses / USD 1															OFF	ON
★ 4 pulses / USD 1															ON	OFF
★ 20 pulses / USD 1															ON	ON

★ Manufacture setting  
Note: After setting dip switch of the credit pulses, you should reset the bill acceptor again.

# S7ER-USD6 (ICT002)

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
★ Reject USD 1	ON															
★ Accept USD 1	OFF															
★ Reject USD 5		ON														
★ Accept USD 5		OFF														
★ Reject USD 10			ON													
★ Accept USD 10			OFF													
★ Reject USD 20				ON												
★ Accept USD 20				OFF												
★ Reject USD 50 & 100					ON											
★ Accept USD 50 & 100					OFF											
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
★ Stack Banknote when Power-up							ON									
★ Reject Banknote when Power-up							OFF									
★ Test Mode (No Communication)								ON								
★ Operation Mode								OFF								
★ Reserved									ON							
★ Reserved									OFF							
★ Reserved										ON						
★ Reserved										OFF						
★ Reserved											ON					
★ Reserved											OFF					
★ Pulse Mode													ON			
★ ICT002 Mode														OFF		
★ Reserved															ON	
★ Reserved																OFF
★ Reserved																ON
★ Reserved																OFF

★ Manufacture setting  
After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note: 1.No RFID function.

## Currency Assign Data

Bill value	Interface	Pulse	ICT002
BV1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5	USD 5
BV3	USD 10	USD 10	USD 10
BV4	USD 20	USD 20	USD 20
BV5	USD 50	USD 50	USD 50
BV6	USD 100	USD 100	USD 100