

S7ER-USD6 Option Switch Settings: (Pulse)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
Reject USD 1	ON															
★ Accept USD 1	OFF															
Reject USD 5		ON														
★ Accept USD 5		OFF														
Reject USD 10			ON													
★ Accept USD 10			OFF													
Reject USD 20				ON												
★ Accept USD 20				OFF												
Reject USD 50 & 100					ON											
★ Accept USD 50 & 100					OFF											
Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
Stack Banknote when Power-up							ON									
★ Reject Banknote when Power-up							OFF									
Inhibit Active HIGH								ON								
★ Inhibit Active LOW								OFF								
Pulse Speed	100ms LO / 100ms HI							ON								
★	50ms LO / 50ms HI							OFF								
Reserve									ON							
★									OFF							
Reserve										ON						
★										OFF						
Reserve											ON					
★											OFF					
Credit-Pulse Normal HIGH										ON						
★										OFF						
Pulse Mode													ON			
★													OFF			
ICT104U Mode																ON
★																OFF
1 pulse / USD 1											OFF	OFF				
★											OFF	ON				
2 pulses / USD 1													ON	OFF		
★													ON	OFF		
4 pulses / USD 1															ON	OFF
★															ON	ON
20 pulses / USD 1																ON
★																ON

★ Manufacture setting
After setting dip switch of the credit pulses, you should reset the bill acceptor again.
Note: 1.No RFID function.

S7ER-USD6 (ICT104U)

S7ER dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4	SW1	SW2	SW3	SW4
Reject USD 1	ON															
★ Accept USD 1	OFF															
Reject USD 5		ON														
★ Accept USD 5		OFF														
Reject USD 10			ON													
★ Accept USD 10			OFF													
Reject USD 20				ON												
★ Accept USD 20				OFF												
Reject USD 50 & 100					ON											
★ Accept USD 50 & 100					OFF											
Disable Bill Reject 4 Times BA Stop By 30 Sec						ON										
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF										
Stack Banknote when Power-up							ON									
★ Reject Banknote when Power-up							OFF									
Test Mode (No Communication)								ON								
★ Operation Mode								OFF								
Reserved									ON							
★									OFF							
Reserved										ON						
★										OFF						
Reserved											ON					
★											OFF					
Reserved												ON				
★												OFF				
Reserved													ON			
★													OFF			
Pulse Mode														ON		
★														OFF		
ICT104U Mode																ON
★																OFF
Reserved																ON
★																OFF
Reserved																
★																ON
Reserved																
★																OFF

★ Manufacture setting
After setting dip switch of the credit pulses, you should reset the bill acceptor again.

Note: 1.No RFID function.

Currency Assign Data

Bill Value	Interface	Pulse	ICT104U
BV1	USD 1	USD 1	1
BV2	USD 5	USD 5	5
BV3	USD 10	USD 10	10
BV4	USD 20	USD 20	20
BV5	USD 50	USD 50	50
BV6	USD 100	USD 100	100