

TAO-A.V-USD6

TAO-A.V Option Switch Settings: 1(Pulse/ICT104V/ICT104U/MDB)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

TAO-A.V dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject USD 1	ON											
★ Accept USD 1	OFF											
★ Reject USD 5		ON										
★ Accept USD 5		OFF										
★ Reject USD 10			ON									
★ Accept USD 10			OFF									
★ Reject USD 20				ON								
★ Accept USD 20				OFF								
★ Reject USD 50 & 100					ON							
★ Accept USD 50 & 100					OFF							
★ Reserved						ON						
★ Reserved						OFF						
★ Harness Disable							ON					
★ Harness Enable							OFF					
★ Inhibit Active High								ON				
★ Inhibit Active Low								OFF				
★ 1 pulse / USD 1									OFF	OFF		
★ 2 pulses / USD 1									ON	OFF		
★ 4 pulses / USD 1									OFF	ON		
★ 20 pulses / USD 1									ON	ON		
★ Interface Timing Conversion	50ms LO / 50ms HI									OFF	OFF	
	60ms LO / 300ms HI									ON	OFF	
	30ms LO / 50ms HI									OFF	ON	
	150ms LO / 150ms HI									ON	ON	

★ Manufacture setting

◆ Note : (1) Default setting.

(2) Use 2nd and 3rd dip of the internal dip-switch to change different interface protocol.

(3) Remove the front cover and the dip-switch in on the CPU board.

(Please refer to "SW1" setting.)

Appendix

TAO-A.V-USD6(Pulse/ICT104V/ICT104U/MDB)

Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON	OFF	
ICT104V Interface		OFF	ON	
ICT104U Interface		OFF	OFF	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Interface Settings: 2(ICT104V)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
ICT104U Interface		OFF	OFF	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

Currency Assign Data

Interface Bill value	ICT104U	Pulse	MDB	ICT104V
BV1	USD 1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5		USD 5
BV3	USD 10	USD 10	USD 5	USD 10
BV4	USD 20	USD 20	USD 10	USD 20
BV5	USD 50	USD 50	USD 20	USD 50
BV6	USD 100	USD 100	USD 50	USD 100
BV7			USD 100	

Interface Settings: 2(ICT104U)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
Reserved	OFF			
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
★ ICT104U Interface		OFF	OFF	
MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting

TAO-V-USD6 Interface Settings: 2(MDB)

FUNCTION	SW1	SW2	SW3	SW4
★ Scaling Factor (SF) = 100 Decimal Point Position (DPP) = 2	ON			
	OFF			
Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0				
Pulse Mode		ON	OFF	
★ ICT104V Interface		OFF	ON	
★ ICT104U Interface		OFF	OFF	
★ MDB Interface		ON	ON	
★ Reserved				ON
				OFF

★ Manufacture setting