

## XBA mini-USD6

### XBA mini Option Switch Settings: 1(Pulse/ICT-BC)

Supported bill USD 1, 5, 10, 20, 50, 100 6bills.

XBA mini dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject USD 1	ON											
★ Accept USD 1	OFF											
★ Reject USD 5		ON										
★ Accept USD 5		OFF										
★ Reject USD 10			ON									
★ Accept USD 10			OFF									
★ Reject USD 20				ON								
★ Accept USD 20				OFF								
★ Reject USD 50 & 100					ON							
★ Accept USD 50 & 100					OFF							
★ Disable Bill Reject 4 Times BA Stop By 30 Sec						ON						
★ Enable Bill Reject 4 Times BA Stop By 30 Sec						OFF						
★ Colorful light							OFF	OFF				
★ The green light flashes							OFF	ON				
★ Reserved							ON	OFF				
★ No light							ON	ON				
★ Inhibit Active High									ON			
★ Inhibit Active Low									OFF			
★ Reserved										ON		
★ Reserved										OFF		
★ Interface Timing Conversion						50ms LO / 50ms HI					OFF	OFF
						60ms LO / 300ms HI					ON	OFF
						30ms LO / 50ms HI					OFF	ON
						150ms LO / 150ms HI					ON	ON

★ Manufacture setting

Note : (1) After setting dip switch of the credit pulses, you should reset the bill acceptor again.

(2) Calibration card is needed.

(3) ICT BC Protocol supports USB and RS-232

## XBA mini-USD6(Pulse/ICT-BC)

### Interface Settings: 2(Pulse)

INTERFACE	SW1	SW2	SW3	SW4
★ Credit-Pulse Normal HIGH	ON			
Credit-Pulse Normal LOW	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ 1 pulse / USD 1			OFF	OFF
2 pulses / USD 1			OFF	ON
4 pulses / USD 1			ON	OFF
20 pulses / USD 1			ON	ON

★ Manufacture setting

### Interface Settings: 2(ICT-BC)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
★ Pulse Mode		ON		
★ Other Mode		OFF		
★ Reserved			OFF	OFF
★ Reserved			OFF	ON
★ ICT-BC Mode			ON	OFF
★ Reserved			ON	ON

★ Manufacture setting

### Currency Assign Data

Interface Bill value	Pulse	ICT-BC
BV1	1	1
BV2	5	5
BV3	10	10
BV4	20	20
BV5	50	50
BV6	100	100