

## **Firmware Version 1.0.6 for Zoom 3G Desktop Router Model 4501**

---

### **How to Apply the Firmware Upgrade**

**Important Note:** We recommend that you take note of any changes you made to the router's configuration pages in case these settings are lost during the firmware upgrade process.

- 1** Connect a computer directly into the Zoom 3G Router's **LAN** port via an Ethernet cable. Do not attempt to carry out the firmware upgrade over a wireless connection or through another router or network device!
- 2** Open a web browser and type **http://192.168.1.1** (the router's default LAN IP address) in the address bar. Press **Enter**.
- 3** When the **Status** page appears, type **admin** in the **System Password** field at the top of the page, and then click **Login**.
- 4** Click the **Advanced** icon at the top of the page.
- 5** Click the **Toolbox** icon.
- 6** On the **Toolbox** page, in the left column, click **Firmware Upgrade**.
- 7** On the **Firmware Upgrade** page, click **Browse**.
- 8** On the **Choose File** dialog box, navigate to and select the **20100107\_Zoom\_CDW530\_W1.0.6.bin** file, and then click **Open**.
- 9** You will be returned to the **Firmware Upgrade** page. Click **Upgrade**.
- 10** The firmware upgrade will take about 90 seconds to load and then the router will restart automatically. Please wait about 2 minutes for this entire process to complete.