

# L70-USD6

## L70/P5 DIP SWITCHES SETTING : 1(ICT104U/Pulse)

Supported bill US\$ 1, 5, 10, 20, 50, 100 6 bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★ 1 Pulse / US\$ 1	OFF	OFF	OFF							
2 Pulse / US\$ 1	OFF	OFF	ON							
3 Pulse / US\$ 1	OFF	ON	OFF							
4 Pulse / US\$ 1	OFF	ON	ON							
5 Pulse / US\$ 1	ON	OFF	OFF							
10 Pulse / US\$ 1	ON	OFF	ON							
20 Pulse / US\$ 1	ON	ON	OFF							
100 Pulse / US\$ 1	ON	ON	ON							
Fast output Pulse Lo= 50ms Hi=100ms				ON						
★ Slow output Pulse Lo= 50ms Hi=300ms				OFF						
Inhibit level Active Low				ON						
★ Inhibit level Active High				OFF						
★ Accept US\$ 1 & 5					ON					
Reject US\$ 1 & 5					OFF					
★ Accept US\$ 10						ON				
Reject US\$ 10						OFF				
★ Accept US\$ 20							ON			
Reject US\$ 20							OFF			
★ Accept US\$ 50								ON		
Reject US\$ 50								OFF		
★ Accept US\$ 100									ON	
Reject US\$ 100									OFF	

★ Manufacture setting

Note: (1) Please reset the bill acceptor after set the dip switch.

(2) Dip switches 1 to 5 are only used for pulse protocol.

## DIP SWITCHES SETTING : 2

FUNCTION	SW1	SW2	SW3	SW4
★ Credit - Pulse Normal High	ON			
Credit - Pulse Normal Low	OFF			
★ Pulse Mode		ON		
ICT104U Interface Mode		OFF		
Reserved			ON	
★ Reserved			OFF	
Reserved				ON
★ Reserved				OFF

## Currency Assign Data

Interface Bill value	Pulse	ICT
BV1	US \$ 1	US \$ 1
BV2	US \$ 5	US \$ 5
BV3	US \$ 10	US \$ 10
BV4	US \$ 20	US \$ 20
BV5	US \$ 50	US \$ 50
BV6	US \$100	US \$100