

# NE77-USD3

## NE77 DIP SWITCHES SETTING : (Pulse/MDB/ICT104U)

Supported bill USD 1, 5, 10 3bills.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10	
★ Accept USD 1	ON										
Reject USD 1	OFF										
★ Accept USD 5		ON									
Reject USD 5		OFF									
★ Accept USD 10			ON								
Reject USD 10			OFF								
★ Reserved				ON							
Reserved				OFF							
★ Reserved					ON						
Reserved					OFF						
★ Reserved						ON					
Reserved						OFF					
★ Inhibit level Active Low	Scaling Factor (SF) =100 (MDB only) Decimal Point Position (DPP) = 2						ON				
Inhibit level Active High	Scaling Factor (SF) = 1 Decimal Point Position (DPP) = 0						OFF				
★ Pulse Normal High								ON			
Pulse Normal Low								OFF			
★ MDB Mode									OFF	OFF	
Reserved									OFF	ON	
ICT104U Mode									ON	OFF	
Pulse Mode									ON	ON	

(★) Manufacture setting

Note.(1) Please reset the bill acceptor after set the dip switch.

(2) Pulse speed is LO=50ms/HI=100ms.

### Currency Assign Data

Interface Bill value	Pulse	MDB	ICT104U
BV1	USD 1	USD 1	USD 1
BV2	USD 5	USD 5	USD 5
BV3	USD 10	USD 10	USD 10