

SCA1-GBP5

SCA1 DIP SWITCHES SETTING : 1(Pulse/Parallel/RS232)

Supported coin GBP 0.1, 0.2, 0.5, 1, 2, 5 coins.

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6
★ Pulse (25ms)	OFF	OFF				
Pulse (45ms)	ON	OFF				
Pulse (60ms)	OFF	ON				
Pulse (100ms)	ON	ON				
★ Accept GBP 0.1, 0.2, 0.5			ON			
Reject GBP 0.1, 0.2, 0.5			OFF			
★ Accept GBP 1				ON		
Reject GBP 1				OFF		
★ Accept GBP 2					ON	
Reject GBP 2					OFF	
★ Normal Open						ON
Normal Close						OFF

★ Manufacture setting

Currency Assign Data

Channel Currency	Paralle	Coin : Credit Normal Pulse
Channel 1 : \$0.1	3	1 : 1
Channel 2 : \$0.1	3	1 : 1
Channel 3 : \$0.2	4	1 : 2
Channel 4 : \$0.5	5	1 : 5
Channel 5 :		
Channel 6 : \$2	2	1 : 20
Channel 7 : \$1(N)	1	1 : 10