

## V6E-USD4

### V6E Option Switch Settings: 1 (MDB)

Supported bill US\$ 1, 5, 10, 20 4bills.

V6E dip-switch settings and functions:

FUNCTION	SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW1	SW2	SW3	SW4
★ Reject US\$ 1	ON											
★ Accept US\$ 1	OFF											
★ Reject US\$ 5		ON										
★ Accept US\$ 5		OFF										
★ Reject US\$ 10			ON									
★ Accept US\$ 10			OFF									
★ Reject US\$ 20				ON								
★ Accept US\$ 20				OFF								
★ Reserved					ON							
★ Reserved					OFF							
★ High Acceptance						ON						
★ High Security						OFF						
★ Reserved							ON					
★ Reserved							OFF					
★ Reserved								ON				
★ Reserved								OFF				
★ Reserved									ON			
★ Reserved									OFF			
★ Reserved										ON		
★ Reserved										OFF		
★ Reserved											ON	
★ Reserved											OFF	
★ Reserved												ON
★ Reserved												OFF

★ Manufacture setting

◆ Default setting (Factory configuration has all switches in the OFF position.)

Note : (1) Reset the bill acceptor after setting the dip switch.

## V6E-USD4(MDB)

Remove the front cover and the dip-switch is on the CPU board.

### V6E Interface Settings: 2 (MDB)

INTERFACE	SW1	SW2	SW3	SW4
★ Reserved	ON			
★ Reserved	OFF			
★ Reserved		ON		
★ MDB Interface		OFF		
★ Reserved			ON	
★ Reserved			OFF	
★ Reserved				ON
★ Reserved				OFF

★ Manufacture setting

### Currency Assign Data

Interface Bill value	MDB
BV1	US\$ 1
BV3	US\$ 5
BV4	US\$ 10
BV5	US\$ 20