

Poggie

Overview :

Pin Out :

Pin 1 is denoted by the square solder pad.

- 1 = Red Wire (+5VDC from the power supply)
There is also another Red wire punched down for use with a meter. (Meter +)
- 2 = Black Wire (Ground from power supply)
- 3 & 4 = Brown Wires Key Switch in pin 3 is ground pin4 = pulse in
- 5 = Violet (Coin pulse out)
- 6 = Blue (Meter -) for count meter. Use with 5VDC from pin 1

Woggie Plus Key Switch Software					
Description	Value (Mode 2)	DIP Switch			
		1	2	3	4
Pulses Out per Pulse In	1 (1)	0	0	0	
	2 (2)	1	0	0	
	4 (4)	0	1	0	
	5 (5)	1	1	0	
	10 (10)	0	0	1	
	20 (20)	1	0	1	
	25 (40)	0	1	1	
	100 (80)	1	1	1	
Pulse Timing ON/OFF	50 / 50				0
	75 / 100				1

The Mode 1 jumper is installed if using a manual button or key switch.
The Mode 2 jumper enables the alternate set of pulse out values.